

Amendment to the Claims:

This listing of claims will replace all prior versions and listings of claims in the application.

1. **(Currently Amended)** An apparatus, comprising:

charge storage circuitry to maintain a first amplitude of a first interrelated control signal and a second amplitude of a second interrelated control signal;

amplitude circuitry coupled to said charge storage circuitry to increase the first amplitude at a rate substantially equivalent to a rate of decrease in the second amplitude, to change an amplitude contribution of a reference clock phase, within high and low amplitude boundaries of a substantially small signal region of a transfer characteristic of phase control circuitry of a phase interpolator; **and**

reference circuitry coupled with comparison circuitry to provide a high voltage boundary for the first amplitude and a low voltage boundary for the second amplitude.

2. (Original) The apparatus of claim 1, further comprising common mode feedback circuitry coupled with said charge storage circuitry to maintain a substantially consistent common mode voltage between the first amplitude and the second amplitude.

3. (Original) The apparatus of claim 2, wherein the common mode feedback circuitry comprises

circuitry to compare the common mode voltage with a reference voltage; and
an output coupled to charge circuitry to increase the first amplitude and the second amplitude in response to the common mode voltage being less than the reference voltage, and coupled to discharge circuitry to decrease the first amplitude and the second amplitude in response to the common mode voltage being greater than the reference voltage.

4. (Original) The apparatus of claim 2, wherein the common mode feedback circuit comprises discrete time circuitry to output charging and discharging pulses for the first interrelated control signal and the second interrelated control signal.

5. (Original) The apparatus of claim 2, wherein the common mode feedback circuit comprises circuitry to facilitate a domination of an increase in the first amplitude over a decrease in the second amplitude.
6. (Cancelled)
7. (Currently Amended) The apparatus of claim [[6]] 1, wherein the reference circuitry comprises a resistive ladder.
8. (Currently Amended) The apparatus of claim [[6]] 1, wherein the reference circuitry further comprises a middle reference voltage to provide a reference for a common mode voltage between the first amplitude and the second amplitude.
9. (Original) The apparatus of claim 1, further comprising a leakage compensation circuit coupled with a capacitance circuit of said charge storage circuitry to compensate for differences in leakage of charge.
10. (Original) The apparatus of claim 9, wherein the leakage compensation circuit comprises an impedance to couple the capacitance circuit with a voltage supply node.
11. (Original) The apparatus of claim 1, wherein said charge storage circuitry comprises a capacitance circuit to provide a differential interrelated control signal for the reference clock phase.
12. (Original) The apparatus of claim 1, wherein said charge storage circuitry comprises a first capacitance circuit to store a first charge and a second capacitance circuit to store a second charge, wherein the first charge is substantially equivalent to the first amplitude and the second charge is substantially equivalent to the second amplitude.
13. (Original) The apparatus of claim 12, wherein said amplitude circuitry comprises a differential current-steering mechanism coupled to said charge storage circuitry to charge the first capacitance circuit and discharge the second capacitance circuit.

14. (Original) The apparatus of claim 1, wherein said amplitude circuitry comprises:
charging circuitry to increase the first amplitude; and
discharging circuitry to decrease the second amplitude in proportion to an increase in the first amplitude.
15. (Original) The apparatus of claim 1, wherein said amplitude circuitry comprises:
trip high circuitry to compare the first amplitude to a high amplitude boundary; and
trip low circuitry to compare the second amplitude to a low amplitude boundary.
16. (Original) The apparatus of claim 15, wherein said amplitude circuitry comprises:
an overflow output to output an overflow signal in response to a charge stored by said charge storage circuitry; and
hysteresis circuitry to prevent chatter in the overflow signal in response to the charge stored by said charge storage circuitry.
17. (Previously Presented) A method, comprising:
receiving a signal to transition a phase of an interpolated clock signal;
increasing an amplitude of a first interrelated control signal in response to said receiving a signal, to increase an amplitude contribution of a first reference clock phase;
decreasing an amplitude of a second interrelated control signal substantially simultaneously with said increasing an amplitude, to decrease an amplitude contribution of a second reference clock phase in proportion to the increase in the amplitude contribution of the first reference clock phase;
bounding the amplitudes of the first interrelated control signal and the second interrelated control signal between a high amplitude boundary and a low amplitude boundary, to change the phase of the interpolated clock signal with a substantially analog transition; and
compensating for leakage of charge.
18. (Original) The method of claim 17, further comprising maintaining a common mode amplitude of the first interrelated control signal and the second interrelated control signal.
19. (Cancelled)

20. (Original) The method of claim 17, wherein said receiving a signal to transition the phase of the interpolated clock signal comprises receiving a signal to instruct charge circuitry to charge a first charge storage circuit associated with the first interrelated control signal and to discharge a second charge storage circuit associated with the second interrelated control signal.

21. (Original) The method of claim 17, wherein said increasing an amplitude comprises charging a first charge storage circuit to increase the amplitude contribution of the first reference clock phase.

22. (Original) The method of claim 17, wherein said decreasing an amplitude comprises discharging a second charge storage circuit to decrease the amplitude contribution of the second reference clock phase.

23. (Original) The method of claim 17, wherein said bounding the amplitudes comprises outputting an overflow signal to indicate that an amplitude of the amplitudes is substantially near at least one of the boundaries.

24. (Original) The method of claim 23, wherein outputting an overflow signal comprises outputting an overflow signal based on a hysteresis range of amplitudes to prevent chatter in the overflow signal.

25. (Currently Amended) A system, comprising:
circuitry to clock data with an interpolated clock signal;
a phase interpolator to generate the interpolated clock signal based upon a first interrelated control signal and a second interrelated control signal, **wherein the phase interpolator comprises a degenerative mesh to flatten a change in bias current associated with a change in the amplitude of the first interrelated control signal**; and
a phase controller coupled to said phase interpolator, comprising
charge storage circuitry to maintain a first amplitude of the first interrelated control signal and a second amplitude of the second interrelated control signal;
amplitude circuitry coupled to said charge storage circuitry to increase the first amplitude at a rate substantially equivalent to a rate of decrease in the second amplitude, to change an amplitude contribution of a reference clock phase, within high and low amplitude boundaries of

a substantially small signal region of a transfer characteristic of phase control circuitry of said phase interpolator.

26. **(Cancelled)**

27. **(Original)** The system of claim 25, wherein the amplitude circuitry comprises:
charging circuitry to increase the first amplitude; and
discharging circuitry to decrease the second amplitude in substantially inverse proportion to an increase in the first amplitude.

28. **(Currently Amended)** A ~~machine-readable~~ **computer-readable** medium containing instructions, which when executed by a ~~machine~~ **computer**, cause said ~~machine~~ **computer** to perform operations, comprising:

receiving a signal to transition a phase of an interpolated clock signal;
increasing an amplitude of a first interrelated control signal in response to said receiving a signal, to increase an amplitude contribution of a first reference clock phase;

decreasing an amplitude of a second interrelated control signal substantially simultaneously with said increasing an amplitude, to decrease an amplitude contribution of a second reference clock phase in proportion to the increase in the amplitude contribution of the first reference clock phase;

bounding the amplitudes of the first interrelated control signal and the second interrelated control signal between a high amplitude boundary and a low amplitude boundary, to change the phase of the interpolated clock signal with a substantially analog transition; and
compensating for leakage of charge.

29. **(Currently Amended)** The ~~machine-readable~~ **computer-readable** medium of claim 28, wherein said increasing an amplitude comprises charging a first charge storage circuit to increase the amplitude contribution of the first reference clock phase.

30. **(Currently Amended)** The ~~machine-readable~~ **computer-readable** medium of claim 28, wherein said decreasing an amplitude comprises discharging a second charge storage circuit to decrease the amplitude contribution of the second reference clock phase.